

OPPO BDP-83 Settings Checklist

version 9

Options are in [brackets], Reset Factory Default values are in **bold**.

For more information, see the [online manual](#) and [FAQ](#).

Setup Wizard

Primary video output [**HDMI** | Component]
Output Resolution [**Auto** | 1080p | 1080i | 720p | 480p/576p | 480i/576i | Source Direct]
Aspect Ratio [4:3 Letterbox | 4:3 Pan & Scan | **16:9 Wide** | 16:9 Wide/Auto]
Audio Setting [**Compatible** | Advanced]

Playback Setup

SACD Priority [**Multi-Channel** | Stereo | CD Mode]
DVD-Audio Mode [**DVD-Audio** | DVD-Video]
Auto Play Mode [**On** | Off] (*this applies only to audio discs*)
PBC [**On** | Off] (*this applies only to old VCD/SVCD discs*)
Parental Control (*none of these are changed by Reset Factory Default*)
Password [**0 0 0 0**]
BD Ratings [**Off** | 1–21]
DVD Ratings [**Off** | Kid | G | PG | PG-13 | PGR | R | NC17 | Adult]
Area Code [**United States**]
Change Password

Language

Player Language [**English**]
Disc Menu Language [**English** | French | Spanish | Chinese | Other: _ _ _ _]
Audio Language [**English** | French | Spanish | Chinese | Other: _ _ _ _]
Subtitle Language [Auto | **Off** | English | French | Spanish | Chinese | Other: _ _ _ _]

Video Setup

Picture Adjustment

Brightness [-16-**0**-16]
Contrast [-16-**0**-16]
Hue (Analog) [-16-**0**-16] (*not used for HDMI*)
Saturation [-16-**0**-16]
Detail Enhancement [-16-**0**-16]
Edge Enhancement [-16-**0**-16]
Noise Reduction [**0**-8]
Y/C Delay [-16-**0**-16]
Border Level [**0**-16]

Primary Output [**HDMI** | Component]

TV Aspect Ratio [4:3 Letterbox | 4:3 Pan & Scan | **16:9 Wide** | 16:9 Wide/Auto]
TV System [**NTSC** | PAL | Multi-system]
Output Resolution [**Auto** | 1080p | 1080i | 720p | 480p/576p | 480i/576i | Source Direct]
1080p24 Output [Auto | On | **Off**]
DVD 24p Conversion [On | **Off**]

HDMI Options

De-interlacing Mode [**Auto** | Film Bias Mode | Video Mode | 2:2 Even | 2:2 Odd]
CUE Correction [**Auto** | On | Off]
Color Space [**Auto** | RGB Video Level | RGB PC Level | YCbCr 4:4:4 | YCbCr 4:2:2]
HDMI Deep Color [36 Bits | 30 Bits (dithered) | 30 Bits | Off (dithered) | **Off**]
Demo Mode [On | **Off**]
A/V Sync [**0**-200] (*only for HDMI*)

Display Options

Subtitle Shift [-5-**0**-5]
OSD Position [**0**-5]

OSD Mode [**Normal** | Silent | Remaining]
Angle Mark [**Off** | On]
PIP Mark [**Off** | On]
SAP Mark [**Off** | On]
Screen Saver [**On** | Off | Energy Saver]

Audio Format Setup

Secondary Audio [**On** | Off] (*default=Off when Setup Wizard: Advanced*)
HDMI Audio [**Auto** | LPCM | Bitstream | Off] (*default=Bitstream when Setup Wizard: Advanced*)
SACD Output [**PCM** | DSD] (*default=DSD when Setup Wizard: Advanced*)
HDCD Decoding [**On** | Off]
Coaxial/Optical Output [**LPCM** | Bitstream] (*default=Bitstream when Setup Wizard: Advanced*)
LPCM Rate Limit [**48k** | 96k | 192k] (*default=192k when Setup Wizard: Advanced*)
(*LPCM Rate Limit applies only to Coaxial/Optical Output*)

Audio Processing

Speaker Configuration (*these apply only to 5.1/7.1 multichannel*)

FL

Size [**Small** | Large]
Distance [0-**12**-60] (*same as FR*)
Trim [-10.0-**0.0**-10.0]

SW

Size [**On** | Off]
Distance [0-**12**-60] (*limited by the distance of the front speakers*)
Trim [-10.0-**0.0**-10.0]

C

Size [**Small** | Large | Off]
Distance [0-**12**-60] (*limited by the distance of the front speakers*)
Trim [-10.0-**0.0**-10.0]

FR

Size [**Small** | Large]
Distance [0-**12**-60] (*same as FL*)
Trim [-10.0-**0.0**-10.0]

SR

Size [**Small** | Large | Off]
Distance [0-**12**-60] (*same as SL, limited by the distance of the front speakers*)
Trim [-10.0-**0.0**-10.0]

SBR

Size [**Small** | Large | Off]
Distance [0-**12**-60] (*same as SBL, limited by the distance of the front speakers*)
Trim [-10.0-**0.0**-10.0]

SBL

Size [**Small** | Large | Off]
Distance [0-**12**-60] (*same as SBR, limited by the distance of the front speakers*)
Trim [-10.0-**0.0**-10.0]

SL

Size [**Small** | Large | Off]
Distance [0-**12**-60] (*same as SR, limited by the distance of the front speakers*)
Trim [-10.0-**0.0**-10.0]

Down Mix Mode [LT/RT | Stereo | 5.1ch | **7.1ch**]

Dynamic Range Control [**Auto** | On | Off]

Device Setup

Firmware Information

Firmware Upgrade

Firmware Notification [**On** | Off]

Remote Control Code [**Code 1** | Code 2 | Code 3 | Alt. Code]

(remote code is not changed by Reset Factory Default)

HDMI CEC [On | Limited | **Off**]

Dimmer Control [**On** | Dim | Off]

Persistent Storage

Storage Device [**Internal Flash** | USB Drive]

Total Space

Available Space

Erase BD-Video Data

Reset Factory Default

Network Setup

IP Configuration [**Auto (DHCP)** | Manual]

IP Address [_ . _ . _ . _] *(only when IP Configuration=manual)*

Subnet Mask [_ . _ . _ . _] *(only when IP Configuration=manual)*

Gateway [_ . _ . _ . _] *(only when IP Configuration=manual)*

DNS 1 [_ . _ . _ . _] *(only when IP Configuration=manual)*

DNS 2 [_ . _ . _ . _] *(only when IP Configuration=manual)*

BD-Live Network Access [On | Limited | **Off**]

Connection Test

Mac Address

Change Log

2010.05.06: version 9

BD-Live defaults to Off in firmware 50-0424

2010.01.06: version 8

added HDCD decoding

2009.12.17: version 7

adjustments for new Setup Menu layout

2009.11.14: version 6

updated the speaker names

2009.10.04: version 5

removed Dolby Pro Logic II

2009.08.28: version 4

Added Deep Color dither options